

Wireless Door Window Magnetic Sensor

TECHNICAL SPECIFICATION

DOOR/WINDOWS SENSOR

Operation voltage	DC6V (CR2016 3V * 2PCS)
Standby current	≤8uA
Working current	≤10mA
Working indicator	Red LED
Working frequency	433.92Mhz
Low battery	Blue LED, blink every 2s
Value setting for low battery	4.4V ±5%. When battery low than 4.4V, blue LED indicator will blink every 2s, and also the signal of low battery will send out by following the frequency of "heartbeat" (sending sequence of the signal: low voltage signal + heartbeat signal)
Transmitting distance	30-50 meters indoor,100 meters in the open area.



MODEL: L-SAWDS



**Motion
Detection**